

## メートルサイズ ラジアル深溝玉軸受(フランジ付き)

内径 1mm~5mm

形式番号	ISO/JIS	内径		外径		幅 B, C (mm)	基本動定格荷重 Cr (N)	基本静定格荷重 Cor (Newtons)
		d (mm)	D (mm)	D (mm)	D (mm)			
LF-310	F681	1	3	1	3	1	80	23
LF-415	F68/1.5	1.5	4	1.2	4	1.2	125	38
RF-515	F69/1.5	1.5	5	2	5	2	184	57
RF-515ZZ	F69/1.5ZZ	1.5	5	2.6	5	2.6	184	57
RF-615	F60/1.5	1.5	6	2.5	6	2.5	324	97
RF-615ZZ	F60/1.5ZZ	1.5	6	3	6	3	324	97
LF-520	F682	2	5	1.5	5	1.5	187	59
LF-520ZZ	F682ZZ	2	5	2.3	5	2.3	187	59
RF-620	F692	2	6	2.3	6	2.3	330	99
RF-620ZZ	F692ZZ	2	6	3	6	3	330	99
RF-720	F602	2	7	2.8	7	2.8	380	126
RF-720ZZ	F602ZZ	2	7	3.5	7	3.5	380	126
LF-625	F68/2.5	2.5	6	1.8	6	1.8	206	73
LF-625ZZ	F68/2.5ZZ	2.5	6	2.6	6	2.6	206	73
RF-725	F69/2.5	2.5	7	2.5	7	2.5	380	126
RF-725ZZ	F69/2.5ZZ	2.5	7	3.5	7	3.5	380	126
RF-825	F60/2.5	2.5	8	2.8	8	2.8	553	176
RF-825ZZ	F60/2.5ZZ	2.5	8	4	8	4	553	176
LF-630	F673	3	6	2	6	2	206	73
LF-630ZZ	F673ZZ	3	6	2.5	6	2.5	206	73
LF-730	F683	3	7	2	7	2	384	129
LF-730ZZ	F683ZZ	3	7	3	7	3	384	129
RF-1030	F623	3	10	4	10	4	641	226
RF-1030ZZ	F623ZZ	3	10	4	10	4	641	226
RF-830	F693	3	8	3	8	3	553	176
RF-830ZZ	F693ZZ	3	8	4	8	4	553	176
RF-930	F603	3	9	3	9	3	634	219
RF-930ZZ	F603ZZ	3	9	5	9	5	634	219
RF-930ZZY04	F603ZZ	3	9	4	9	4	634	219
LF-1040	-	4	10	3	10	3	708	266
LF-1040ZZ	-	4	10	4	10	4	708	266
LF-740	F674	4	7	2	7	2	252	106
LF-740ZZ	F674ZZ	4	7	2.5	7	2.5	252	106
LF-840	-	4	8	2	8	2	391	140
LF-840ZZ	-	4	8	3	8	3	391	140
LF-940	F684	4	9	2.5	9	2.5	641	226
LF-940ZZ	F684ZZ	4	9	4	9	4	641	226
RF-1140	F694	4	11	4	11	4	714	276
RF-1140ZZ	F694ZZ	4	11	4	11	4	714	276
RF-1240	F604	4	12	4	12	4	959	347
RF-1240ZZ	F604ZZ	4	12	4	12	4	959	347
RF-1340	F624	4	13	5	13	5	1306	487
RF-1340ZZ	F624ZZ	4	13	5	13	5	1306	487
RF-1640	F634	4	16	5	16	5	1735	671
RF-1640ZZ	F634ZZ	4	16	5	16	5	1735	671
LF-1050	-	5	10	3	10	3	714	276
LF-1050ZZ	-	5	10	4	10	4	714	276
LF-1150	F685	5	11	3	11	3	714	276
LF-1150ZZ	F685ZZ	5	11	5	11	5	714	276
LF-850	F675	5	8	2	8	2	274	130
LF-850ZZ	F675ZZ	5	8	2.5	8	2.5	274	130
LF-950	-	5	9	2.5	9	2.5	495	207
LF-950ZZ	-	5	9	3	9	3	495	207
RF-1350	F695	5	13	4	13	4	1074	422
RF-1350ZZ	F695ZZ	5	13	4	13	4	1074	422
RF-1450	F605	5	14	5	14	5	1329	508
RF-1450ZZ	F605ZZ	5	14	5	14	5	1329	508
RF-1650	F625	5	16	5	16	5	1735	671
RF-1650HH	F625ZZ	5	16	5	16	5	1735	671
RF-1950	F635	5	19	6	19	6	2805	1060
RF-1950ZZ	F635ZZ	5	19	6	19	6	2805	1060